



CAI 302 – Flarm



Spannungsanschluss 12V für MUX und Flarm




Schwarzes Kabel mit RJ45 mit 12V für MUX und Flarm.

Blaues Kabel mit D-SUB15 HD und RJ45 vom ECW100 zum MUX mit 12V und Daten

Schalter 3 Stellungen für direkte Kommunikation wie programmiert. Hier: A= ECW100 und B= CAI302. Mittelstellung = Fliegen

Adapterkabel CAI302-MUX-PDA 5V(rot) und Daten(grün)



Kombinierte Daten über MUX= CAI302 >GPS+Vario und Flarm > alle Flarmdaten

Das CAI302 kann vom Pocket-PC gesteuert werden.

Adapterkabel CAI302-MUX-PDA



K6-MUX

Der Multiplexer für drei NMEA-Quellen

```

kkk
K6-Team NMEA-Multiplexer HW v.5 SW v.3b build Apr 21 2008
Configuration ID: ""
                Flarm/ECW100  Power in12V    CAI302
+-----+-----+-----+-----+
|         | Input 1 | Input 2 | Input 3 |
+-----+-----+-----+-----+
| E: Enable Mux | Yes     | No      | Yes     |
| B: Baudrate   | auto   | 4800    | 4800    |
| N: NMEA       | No     | No      | No      |
| C: Cksum      | No     | No      | No      |
| S: Sentence   | Pass   | No      | No      |
| P: Special    | 0      | 0       | 0       |
+-----+-----+-----+-----+
| Sentences    | "$PFL" | ""      | ""      |
|              | ""     | ""      | ""      |
| A: Add       | ""     | ""      | ""      |
| D: Delete    | ""     | ""      | ""      |
|              | ""     | ""      | ""      |
|              | ""     | ""      | ""      |
|              | ""     | ""      | ""      |
|              | ""     | ""      | ""      |
+-----+-----+-----+-----+
| O: Output baudrate | 19200 |
+-----+-----+-----+-----+
| F: Flight forward menu
| M: Communication menu
| U: Upload configuration
+-----+-----+-----+-----+
| Data forwarding during flight
+-----+-----+-----+-----+
| O: Output RX data | to Input 3 TX
| I: Input data    | [no forwarding]
+-----+-----+-----+-----+
| M: Main menu
+-----+-----+-----+-----+
| Direct communication selected by J3
+-----+-----+-----+-----+
| A: Communication 1 [1-2] | Output <> Input 1 |
| B: Communication 2 [2-3] | Output <> Input 3 |
| C: Communication 3 [4-5] | Output <> Input 1 |
| D: Communication 4 [5-6] | Output <> Input 1 |
+-----+-----+-----+-----+
| M: Main menu
+-----+-----+-----+-----+
    
```